



Model: G2M

## MIDI Implementation Chart

Version: 2.0

Function...	Transmitted	Recognised	Remarks	
<b>Basic Channel</b>	Default Changed	1 1	X X	
<b>Mode</b>	Default Messages Altered	Mode 4 X X	X X X	
<b>Note Number</b>	True voice	33-94 X	X X	
<b>Velocity</b>	Note On Note Off	O X	X X	
<b>After Touch</b>	Key's Channel	X X	X X	
<b>Pitch Bend</b>		O	X	14-bit ±2 semitone range
<b>Control Change</b>	0-127	123 (All Notes Off)	X	Transmitted at power-on only
<b>Program Change</b>	True Number	X	X	
<b>System Exclusive</b>		X	X	
<b>System Common</b>	Song Position Song Select Tune Request	X X X	X X X	
<b>System Real Time</b>	Clock Commands	X X	X X	
<b>Aux Messages</b>	Local On/Off All Notes Off Active Sensing System Reset	X X X X	X X X X	
<b>Notes</b>	The unit does not receive MIDI, it is only a transmitter.			

Mode1: Omni On, Poly  
Mode3: Omni Off Poly

Mode2: Omni On, Mono  
Mode4: Omni Off, Mono

O:Yes  
X: No

[www.sonus.com](http://www.sonus.com) — for the latest information and details on other **SONUUS** products visit our web site.

**SONUUS, G2M** are Trademarks or Registered Trademarks of Sonuus Limited.

The information contained herein is subject to change without notice.